2.5 GSPS Direct Digital Synthesizer with 12-bit DAC

Preliminary Technical Data

AD9915

FEATURES

2.5 GSPS internal clock speed
Integrated 12-bit DAC
Frequency tuning resolution to 194 pHz
16-bit phase tuning resolution
12-bit amplitude scaling
Programmable Modulus
Automatic linear and nonlinear frequency sweeping capability
32-bit Parallel Data path Interface
8 frequency/phase offset profiles
Phase noise xxx dBc/Hz (10kHz Offset)
Wide band SFDR>50dBc
Serial or Parallel I/O control
1.8V / 3.3 V power supplies
Software and hardware controlled power-down
88-lead LFCSP package
PLL REFCLK multiplier
Phase modulation capability
Amplitude modulation capability
Multichip synchronization

APPLICATIONS

Agile LO frequency synthesis
Programmable clock generator
FM chirp source for radar and scanning systems
Test and measurement equipment
Acousto-optic device drivers
Polar Modulator
Fast Frequency Hopping

FUNCTIONAL BLOCK DIAGRAM



Figure 1.

Rev. PrI
Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

One Technology Way, P.O. Box 9106, Norwood, MA 02062-9106, U.S.A.
Tel: 781.329.4700 www.analog.com
Fax: 781.461.3113
©2012 Analog Devices, Inc. All rights reserved.

GENERAL DESCRIPTION

The AD9915 is a direct digital synthesizer (DDS) featuring a 12-bit DAC. The AD9915 uses advanced DDS technology, coupled with an internal high speed, high performance DAC to form a digitally programmable, complete high frequency synthesizer capable of generating a frequency-agile analog output sinusoidal waveform at up to 1.0 GHz. The AD9915 is enables fast frequency hopping and fine tuning resolution (64-bit capable using programmable modulus mode). The AD9915 also offers fast phase and amplitude hopping capability. The frequency tuning and control words are loaded into the AD9915 via a serial or parallel I/O port. The AD9915 also supports a user defined linear sweep mode of operation for generating linear swept waveforms of frequency, phase or amplitude. A high speed 32-bit parallel data input port is included enabling high data rates for polar modulation schemes and fast reprogramming of the phase, frequency and amplitude tuning words.

The AD9915 is specified to operate over the extended industrial temperature range (see Absolute Max Ratings table).



Figure 2. Detailed Block Diagram

SPECIFICATIONS

DC SPECIFICATIONS

AVDD (1.8V) and DVDD (1.8V) = 1.8 V ± 5%, AVDD (3.3V) and DVDD_I/O (3.3V) = 3.3 V ± 5%, T = 25°C, R_{SET} = 3.3 kΩ, I_{OUT} = 20 mA, external reference clock frequency = 2.5 GHz with reference clock (REFCLK) multiplier bypassed, unless otherwise noted.

Table 1.

Parameter	Min	Typ	Max	Unit	Test Conditions/Comments
SUPPLY VOLTAGE					
DVDD_I/O (Pins 16,83)	3.135	3.30	3.465	V	
DVDD (Pins 6,23,73)	1.71	1.80	1.89	V	
AVDD3 (Pins 34,36,39,40,43,47,50, 52,53,60)	3.135	3.30	3.465	V	
AVDD (Pin 32, Pin 56, Pin 57)	1.71	1.80	1.89	V	
SUPPLY CURRENT					See also the Total Power Dissipation specifications
$I_{DVDD\_I/O}$ (Pins 16, 83)			20	mA	
I_{DVDD} (Pins 6, 23,73)			433	mA	
I_{AVDD3} (Pin 34,36,39,40,43,50,52, 53,60)			564	mA	
I_{AVDD} (Pins 32,47,56,57)			178	mA	
TOTAL POWER DISSIPATION					
Base DDS Power, PLL Disabled		2392	2810	mW	2.5GHz, Single-Tone Mode, Modules Disabled, Linear Sweep Disabled, Amplitude Scaler Disabled.
Base DDS Power, PLL Enabled		2237	2627	mW	2.5GHz, Single-Tone Mode, Modules Disabled, Linear Sweep Disabled, Amplitude Scaler Disabled.
Linear Sweep Additional Power		+28		mW	
Modulus Additional Power		+20		mW	
Amplitude Scaler Additional Power		+138		mW	Manual or Automatic
Full Power-Down Mode		400	550	mW	Using either the power-down and enable register or the PWRDOWN pin
CMOS LOGIC INPUTS					
Input High Voltage (V_{IH})	2.0		DVDD_I/O	V	
Input Low Voltage (V_{IL})			0.8	V	
Input Current (I_{INH}, I_{INL})		±60	±200	µA	At V_{IN} = 0 V and V_{IN} = DVDD_I/O
Maximum Input Capacitance (C_{IN})		3		pF	
CMOS LOGIC OUTPUTS					
Output High Voltage (V_{OH})	2.7		DVDD_I/O	V	I_{OH} = 1 mA
Output High Voltage (V_{OL})			0.4	V	I_{OL} = 1 mA

Parameter	Min	Typ	Max	Unit	Test Conditions/Comments
REFCLK INPUT CHARACTERISTICS					REF CLK inputs should always be ac-coupled (both single-ended and differential)
REFCLK Multiplier Bypassed					
Input Capacitance		1		pF	Single-ended, each pin
Input Resistance		1.4		kΩ	Differential
Internally Generated DC Bias Voltage		2		V	
Differential Input Voltage		0.8	1.5	mV pk	
REFCLK Multiplier Enabled				MHz	
Input Capacitance		1		pF	Single-ended, each pin
Input Resistance		1.4		kΩ	Differential
Internally Generated DC Bias Voltage		2		V	
Differential Input Voltage		0.8	1.5	mV pk	

AC SPECIFICATIONS

AVDD (1.8V) and DVDD (1.8V) = 1.8 V ± 5%, AVDD3 (3.3V) = 3.3 V ± 5%, DVDD_I/O (3.3V) = 3.3 V ± 5%, T = 25°C, R_{SET} = 3.3 kΩ, I_{OUT} = 20 mA, external reference clock frequency = 2.5 GHz with reference clock (REFCLK) multiplier disabled, unless otherwise noted.

Table 1.

Parameter	Min	Typ	Max	Unit	Test Conditions/Comments
REFCLK INPUT					Input Frequency Range
REFCLK Multiplier Bypassed					
Input Frequency Range	100		2500	MHz	Maximum f_{OUT} is 0.4 × f_{SYSCLK}
Duty Cycle	45		55	%	
Minimum Differential Input Level	632			mV p-p	Equivalent to 316 mV swing on each leg
SYSCLK PLL Enabled					
VCO Frequency Range	2400		2500	MHz	
VCO gain		50		MHz/V	
Maximum 2PFD Rate			125	MHz	
CLOCK DRIVERS					
SYNC_CLK Output Driver					
Frequency Range			156	MHz	
Duty Cycle	45	50	55	%	
Rise Time/Fall Time (20% to 80%)		650		ps	10 pF load
SYNC_OUT Output Driver					
Frequency Range			6.5	MHz	
Duty Cycle		50		%	
Rise Time (20% to 80%)		1350		ps	10 pF load
Fall Time (20% to 80%)		1670		ps	10 pF load
DAC OUTPUT CHARACTERISTICS					
Output Frequency Range (1st Nyquist Zone)	0		1250	MHz	
Output Resistance		50		Ω	Single-ended (each pin internally terminated to AVSS)
Output Capacitance		5		pF	
Full-Scale Output Current			20.48	mA	Range depends on DAC R_{SET} resistor
Gain Error	–10		+10	% FS	
Output Offset			0.6	µA	
Voltage Compliance Range	AVDD – 0.50	+0.5	AVDD + 0.50	V	

Parameter	Min	Typ	Max	Unit	Test Conditions/Comments
Wideband SFDR					See the Typical Performance Characteristics section
123.5 MHz Output		-67		dBc	0 MHz to 1750 MHz
305.5 MHz Output		-66		dBc	0 MHz to 1250 MHz
497.5.5 MHz Output		-59		dBc	0 MHz to 1250 MHz
978.5.5 MHz Output		-60		dBc	0 MHz to 1250 MHz
Narrow-Band SFDR					See the Typical Performance Characteristics section
123.5 MHz Output		-95		dBc	±500 kHz
305.5 MHz Output		-95		dBc	±500 kHz
497.5 MHz Output		-95		dBc	±500 kHz
978.5 MHz Output		-92		dBc	±500 kHz
DIGITAL TIMING SPECIFICATIONS					
Time Required to Enter Power-Down				µs	Power Down Mode looses DAC/PLL calibration settings.
Time Required to Leave Power-Down				µs	Must re-calibrate DAC/PLL
Minimum Master Reset time	TBD				
Max DAC Calibration Time			TBD	ms	FCAL = FSYSCLK/384. User 0 register bit 6 =1
Max PLL Calibration Time			TBD	T_CAL	
Synchronization Time			16	SYNC_IN cycles	
Max Profile Pin Toggle Rate			1	SYNC_CLK period	
PARALLEL PORT TIMING					
Write Timing					
Address Setup Time to WRB Active	1			ns	
Address Hold Time to WRB Inactive			0	ns	
Data Setup Time to WRB Inactive	3.8			ns	
Data Hold Time to WRB Inactive			0	ns	
WRB Minimum Low Time			2.1	ns	
WRB Minimum High Time			3.8	ns	
Minimum WRB Time			10.5	ns	
Read Timing					
Address to Data Valid			92	ns	
Address Hold to RDB Inactive			0	ns	
RDB Active to Data Valid			69	ns	
RDB Inactive to Data Tristate			50	ns	
RDB Minimum Low Time			69	ns	
RDB Minimum High Time			50	ns	
SERIAL PORT TIMING					
SCLK Clock Rate ($1/t_{CLK}$)			80	MHz	SCLK Duty Cycle = 50%
SCLK Pulse Wdth High, t_{HIGH}	1.5			ns	
SCLK Pulse Width Low, t_{LOW}	5.1			ns	
SDIO to SCLK Setup Time, t_{DS}	4.9			ns	
SDIO to SCLK Hold Time, t_{DH}			0	ns	
SCLK Falling Edge to Valid Data on SDIO/SDO, t_{DV}			78	ns	
CSB to SCLK Setup Time, t_S	4			ns	
CSB to SCLK Hold Time, t_H			0	ns	
CSB Minimum Pulse Width High, t_{PWH}	4			ns	
DATAPORT PORT TIMING					
D[31:0] Setup Time to SYNC_CLK	2			ns	

Parameter	Min	Typ	Max	Unit	Test Conditions/Comments
D[31:0] Hold Time to SYNC_CLK			0	ns	
F[3:0] Setup Time to SYNC_CLK	2			ns	
F[3:0] Hold Time to SYNC_CLK			0	ns	
IO_UPDATE Pin Setup Time to SYNC_CLK	2			ns	
IO_UPDATE Pin Hold Time to SYNC_CLK			0	ns	
Profile Pin Setup Time to SYNC_CLK	2			ns	
Profile Pin Hold Time to SYNC_CLK			0	ns	
DR_CTL/DR_HOLD Setup Time to SYNC_CLK	2			ns	
DR_CTL/DR_HOLD Hold Time to SYNC_CLK			0	ns	
DATA LATENCY (PIPELINE DELAY)					
Single Tone Mode (Matched Latency Disabled)					SYSCLK Cycles = f_S = system clock frequency in GHz
Frequency		40		SYSCLK cycles	
Phase		37		SYSCLK cycles	
Amplitude		13		SYSCLK cycles	
Single Tone Mode (Matched Latency Enabled)					
Frequency		40		SYSCLK cycles	
Phase		40		SYSCLK cycles	
Amplitude		40		SYSCLK cycles	
Profile Pin Selection Mode					
Frequency		40		SYSCLK cycles	
Phase		37		SYSCLK cycles	
Amplitude		13		SYSCLK cycles	
Modulation Mode w/ 32-bit Parallel Port					
Frequency		37		SYSCLK cycles	
Phase		34		SYSCLK cycles	
Amplitude		10		SYSCLK cycles	
Sweep Mode					
Frequency		49		SYSCLK cycles	
Phase		46		SYSCLK cycles	
Amplitude		22		SYSCLK cycles	

ABSOLUTE MAXIMUM RATINGS

Table 2.

Parameter	Rating
AVDD (1.8V), DVDD (1.8V) Supplies	2 V
AVDD (3.3V), DVDD_I/O (3.3V) Supplies	4 V
Digital Input Voltage	−0.7 V to +4 V
Digital Output Current	5 mA
Storage Temperature Range	−65°C to +150°C
Operating Temperature Range	−40°C to +85°C
θ_{JA}	
θ_{JC}	
Maximum Junction Temperature	150°C
Lead Temperature (10 sec Soldering)	300°C

Stresses above those listed under Absolute Maximum Ratings may cause permanent damage to the device. This is a stress rating only; functional operation of the device at these or any other conditions above those indicated in the operational section of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

EQUIVALENT CIRCUITS

ESD CAUTION

ESD (electrostatic discharge) sensitive device. Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.

THERMAL PERFORMANCE

Symbol	Description	Value[1]	Units
θ_{JA}	Junction-to-Ambient Thermal Resistance (Still Air) Per JEDEC JESD51-2	24.1	°C/W
θ_{JMA}	Junction-to-Ambient Thermal Resistance (1.0 m/s airflow) Per JEDEC JESD51-6	21.3	°C/W
θ_{JMA}	Junction-to-Ambient Thermal Resistance (2.0 m/s air flow) Per JEDEC JESD51-6	20.0	°C/W
θ_{JB}	Junction-to-Board Thermal Resistance (Still Air) Per JEDEC JESD51-8	13.3	°C/W
Ψ_{JB}	Junction-to-Board Characterization Parameter (Still Air) Per JEDEC JESD51-6	12.8	°C/W
θ_{JC}	Junction-to-Case Thermal Resistance	2.21	°C/W
Ψ_{JT}	Junction-to-Top-of-Package Characterization Parameter (Still Air) Per JEDEC JESD51-2	0.23	°C/W

[1] Results are from simulations. PCB is JEDEC multi-layer. Thermal performance for actual applications requires careful inspection of the conditions in the application to determine if they are similar to those assumed in these calculations.

PIN CONFIGURATION AND FUNCTION DESCRIPTIONS



Note: The EPAD must be soldered to GND

Figure 3. Pin Configuration

Table 3. Pin Function Descriptions

Pin No.	Mnemonic	I/O[1]	Description
1-5, 8-15, 18 - 22, 68-72, 75-81, 87,88	D0 – D31	I /O	Multi-purpose parallel port pins.The 32-bit parallel port offers the option for serial or parallel programming of the internal registers. In addition, the parallel port can be configured to provide direct FSK, PSK or ASK (or combinations) modulation data. The 32-bit parallel port configuration is set by the state on the four function pins (F0-F3).
3-5, 8-12	D15 –D9 / A7 – A0	I/O	Multi-purpose pins depending on the state of the function pins (F0-F3). The state of the F0-F3 function pins determine if these lines are address lines for programming the internal registers or lines for direct FSK, PSK, or ASK data.
22	D0 / $\overline{CS}$ / PWD	I	Multi-purpose pin depending on the state of the function pins (F0-F3). This pin is D0 for direct FSK, PSK, or ASK data. If serial mode is invoked via (F0-F3), this pin is used for the Chip Select for serial operation. If parallel mode is enabled, this pin is used to set either 8-bit data or 16 data.
21	D1 / SCLK / RDB	I	Multi-purpose pin depending on the state of the function pins (F0-F3). This pin is D1 for direct FSK, PSK, or ASK data. If serial mode is invoked via (F0-F3), this pin is used for the SCLK for serial operation. If parallel mode is enabled, this pin is used to read back the value of the internal registers.
20	D2 / SDIO / WRB	I/O	Multi-purpose pin depending on the state of the function pins (F0-F3). This pin is D2 for direct FSK, PSK, or ASK data. If serial mode is invoked via (F0-F3), this pin is used for the SDIO for serial operation. If parallel mode is enabled, this pin is used to write to change values of the internal registers.
19	D3 / SDO	I/O	Multi-purpose pin depending on the state of the function pins (F0-F3). This pin is D3 for direct FSK, PSK, or ASK data. If serial mode is invoked via (F0-F3), this pin is used for read back mode for serial operation.
18	D4 / SYNCIO	I	Multi-purpose pin depending on the state of the function pins (F0-F3). This pin is D4 for direct FSK, PSK, or ASK data. If serial mode is invoked via (F0-F3), this pin is used to reset the serial port.
6, 23, 73	DVDD (1.8V)	I	Digital Core VDD, 1.8 V Digital Supplies.
7, 17, 24, 74, 84	DGND	I	Digital Ground.
16, 83	DVDD_I/O (3.3V)	I	Digital Input/Output VDD, 3.3 V Digital Supplies.
32, 56, 57	AVDD (1.8V)	I	Analog Core VDD, 1.8 V Analog Supplies.
33, 35, 37, 38, 44, 46, 49, 51	AGND	I	Analog Ground.
34, 36, 39, 40, 43, 47, 50, 52, 53, 60	AVDD (3.3V)	I	Analog DAC VDD, 3.3 V Analog Supplies.
25, 26, 27	PROFILE[0:2]	I	Profile Select Pins. Digital inputs (active high). Use these pins to select one of eight phase/frequency profiles for the DDS. Changing the state of one of these pins transfers the current contents of all I/O buffers to the corresponding registers. State changes should be set up on the SYNC_CLK pin.
28,29.30,31	F0-F3	I	Function Pins. Digital Inputs. The state of these pins determine if a serial or parallel interface is used. In addition, the function pins determine how the 32-bit Parallel data word is partition for FSK, PSK, or ASK modulation mode.
41	AOUTB	O	DAC Complementary Output Source. Analog output (voltage mode). Internally connected through a 50 Ω resistor to AVDD.
42	AOUT	O	DAC Output Source. Analog output (voltage mode). Internally connected through a 50 Ω resistor to AVDD.
45	DAC_BP	I	DAC bypass pin.
48	DAC_RSET	O	Analog Reference Pin. This pin programs the DAC output full-scale reference current. Attach a 3.3kΩ resistor to AGND.
54	$\overline{REF\_CLK}$	I	Complementary Reference Clock Input. Analog input.
55	REF_CLK	I	Reference Clock Input. Analog input.

Pin No.	Mnemonic	I/O[1]	Description
58	LOOP FILTER	O	External PLL loop filter node.
59	REF	O	Local PLL Power Supply reference pin. Typically 2.05V.
61	SYNC_OUT	O	Digital Output. Used to Synchronize multiple chips together.
62	SYNC_IN	I	Digital Input. Used to Synchronize multiple chips together.
63	DR_CTL	I	Digital Input (active high). Digital Ramp Control. This pin controls the sweep direction (up/down).
64	DR_HOLD	I	Digital Input (active high). Digital Ramp Hold. Pauses the sweep when active.
65	DR_OVER	O	Digital output (active high). Digital Ramp Over. This pin switches to Logic 1 whenever the digital ramp generator reaches its programmed upper or lower limit.
66	OSK	I	Output Shift Keying. Digital input (active high). When the OSK features are placed in either manual or automatic mode, this pin controls the OSK function. In manual mode, it toggles the multiplier between 0 (low) and the programmed amplitude scale factor (high). In automatic mode, a low sweeps the amplitude down to zero, a high sweeps the amplitude up to the amplitude scale factor.
67	EXT_PWR_DWN	I	Digital Input (Active High). External Power-Down, A high level on this pin initiates the currently programmed power-down mode..
82	SYNC_CLK	O	Digital Output (clock). Many of the digital inputs on the chip, such as I/O_UPDATE, PROFILE[2:0], and Parallel Data Port, need to be set up on the rising edge of this signal.
85	MASTER_RESET	I	Digital Input (Active High). Master Reset, Master reset: clears all memory elements and sets registers to default values.
86	I/O_UPDATE	I	Digital input (active high). A high on this pin transfers the contents of the I/O buffers to the corresponding internal registers.
(EPAD)	Exposed Paddle (EPAD)		The EPAD should be soldered to ground.

[1] I = input, O = output.

TYPICAL PERFORMANCE CHARACTERISTICS

Nominal supply voltage; DAC R_{SET} = 3.3 kΩ, 25C, unless otherwise noted.



Figure 4. Wide Band SFDR at 122.4.MHz SYSCLK = 2.5 GHz (SYSCLK PLL Bypassed)



Figure 5. Wide Band SFDR at 305.3MHz SYSCLK = 2.5 GHz (SYSCLK PLL Bypassed)



Figure 6. Wide Band SFDR at 497.5 MHz, SYSCLK = 2.5 GHz (SYSCLK PLL Bypassed)



Figure 7. Narrow Band SFDR at 122.4 MHz, SYSCLK = 2.5 GHz (SYSCLK PLL Bypassed)



Figure 8. Narrow Band SFDR at 305.3MHz, SYSCLK = 2.5 GHz (SYSCLK PLL Bypassed)



Figure 9. Narrow Band SFDR at 497.5 MHz, SYSCLK = 2.5 GHz (SYSCLK PLL Bypassed)



Figure 10. Wide-Band SFDR at 978.2MHz, SYSCLK = 2.5 GHz (SYSCLK PLL Bypassed)



Figure 13. Narrow Band SFDR at 978.2MHz, SYSCLK = 2.5 GHz (SYSCLK PLL Bypassed)



Figure 11. Wide-Band SFDR verses normalized Fout SYSCLK = 2.5 GHz



Figure 14. Absolute Phase Noise Rohde & Schwarz SMA100 Signal Generator at 2.5 GHz and series ADCLK925)



Figure 12. Wide-Band SFDR verses normalized Fout vs SYSCLK SYSCLK = 2.5 GHz to 2.5 GHz



Figure 15. Absolute Phase Noise of DDS output at 2.5 GHz operation)



Figure 16. Absolute Phase Noise curves of normalized REF CLK source to DDS output at 978 MHz (SYSCLK = 2.5GHz).



Figure 19. Absolute Phase Noise curves of DDS output using internal PLL at 2.5 GHz operation.



Figure 17.


File Edit Vertical Horiz/Acq Trig Display Cursors Measure Math Utilities
Tek Run Sample
06 Jun 12 11:42:55
Ch2 1.0V Ω
M 20.0ns 5.0GS/s IT 40.0ps/pt
A Ch2 ⟋ 1.64V

Figure 20. SYNC_OUT at 2.5GHz SYSCLK. SYNC_OUT = SYSCLK / 384



Figure 18. Power Supply Current vs. SYSCLK rate



Figure 21. DAC Calibration Time vs SYSCLK rate



Figure 22. Measured Rising Linear Frequency Sweep



Figure 23. Measured Falling Linear Frequency Sweep

THEORY OF OPERATION

The AD9915 has five modes of operation.

- Single tone
- Profile Modulation
- Digital ramp modulation (linear sweep)
- Parallel data port modulation
- Programmable Modulus mode

The modes define the data source used to supply the DDS with its signal control parameters: frequency, phase, or amplitude. The partitioning of the data into different combinations of frequency, phase, and amplitude is established based on the mode and/or specific control bits and function pins.

Although the various modes are described independently, they can be enabled simultaneously. This provides an unprecedented level of flexibility for generating complex modulation schemes. However, to avoid multiple data sources from driving the same DDS signal control parameter, the device has a built-in priority protocol.

In single tone mode, the DDS signal control parameters come directly from the profile programming registers. In digital ramp modulation mode, the DDS signal control parameters are delivered by a digital ramp generator. In parallel data port modulation mode, the DDS signal control parameters are driven directly into the parallel port.

The various modulation modes generally operate on only one of the DDS signal control parameters (two in the case of the polar modulation format via parallel data port). The un-modulated DDS signal control parameters are stored in programming registers and automatically route to the DDS based on the selected mode.

A separate output shift keying (OSK) function is also available. This function employs a separate digital linear ramp generator that only affects the amplitude parameter of the DDS. The OSK function has priority over the other data sources that can drive the DDS amplitude parameter. As such, no other data source can drive the DDS amplitude when the OSK function is enabled.

SINGLE TONE

In single tone mode, the DDS signal control parameters are supplied directly from the profile programming registers. A profile is an independent register that contains the DDS signal control parameters. Eight profile registers are available. Note, the profile pins must point the desired profile to output.

PROFILE TONE MODULATION

Each profile is independently accessible. For FSK, PSK, ASK modulation, use the three external profile pins (PROFILE[2:0]) to select the desired profile. A change in the state of the profile pins with the next rising edge on SYNC_CLK updates the DDS with the parameters specified by the selected profile. Therefore the profile change must meet the setup and hold times to the SYNC_CLK rising edge. Note, amplitude control must also be enabled using the OSK EN bit in register CFR1.

DIGITAL RAMP MODULATION MODE

In digital ramp modulation mode, the modulated DDS signal control parameter is supplied directly from the digital ramp generator (DRG). The ramp generation parameters are controlled through the serial or parallel I/O port.

The ramp generation parameters allow the user to control both the rising and falling slopes of the ramp. The upper and lower boundaries of the ramp, the step size and step rate of the rising portion of the ramp, and the step size and step rate of the falling portion of the ramp are all programmable.

The ramp is digitally generated with 32-bit output resolution. The 32-bit output of the DRG can be programmed to affect frequency, phase, or amplitude. When programmed for frequency, all 32 bits are used. However, when programmed to for phase or amplitude, only the 16 MSBs or 12 MSBs, respectively, are used.

The ramp direction (rising or falling) is externally controlled by the DRCTL pin. An additional pin (DRHOLD) allows the user to suspend the ramp generator in its present state. Note, amplitude control must also be enabled using the OSK EN bit in register CFR1

PARALLEL DATA PORT MODULATION MODE

In parallel data port modulation mode, the modulated DDS signal control parameter(s) are supplied directly from the 32-bit parallel data port. The Function pins define how the 32-bit data-word is applied to the DDS signal control parameters. Formatting of the 32-bit data-word is unsigned binary, regardless of the destination.

Parallel Data Clock (SYNC_CLK)

The AD9915 generates a clock signal on the SYNC_CLK pin that runs at 1/24 of the DAC sample rate (the sample rate of the parallel data port). SYNC_CLK serves as a data clock for the parallel port.

PROGRAMMABLE MODULUS MODE

In programmable modulus mode, the DRG is used as an auxiliary accumulator to alter the frequency equation of the DDS core, making it possible to implement fractions which are not restricted to a power of 2 in the denominator.

A standard DDS is restricted to powers of 2 as a denominator because the phase accumulator is a set of bits as wide as the frequency tuning word. When in programmable modulus mode, the frequency equation becomes

$$f_0 = (FTW)(f_S)/x \text{ with } 0 \le FTW \le 2^{31}$$

$f_0 = f_S \times (1 - (FTW/x))$ with $2^{31} < FTW < 2^{32} - 1$

where $2 \leq x \leq 2^{32}$.

When in programmable modulus mode, the auxiliary accumulator is set up to roll over before it reaches full capacity. Every time it rolls over, an extra LSB value is added to the phase accumulator. In order to determine the values that must be programmed in the registers, the user must define the desired output to sampling clock frequency as a ratio of integers (M/N, where N must not exceed 2^{32}). N should be programmed into Register 0x04 [31:0].Register 0x05 [31:0] must be programmed with the FTW which is the integer portion of $((2^{32} \times f_0)/f_S)$. Finally, Register 0x06 [31:0] must be programmed with the modulus step which is the remainder of $((2^{32} \times f_0)/f_S)$.

Note that if the auxiliary accumulator is set to roll over at full capacity it has essentially been appended to the phase accumulator, resulting in a DDS with a 64 bit tuning word

FUNCTIONAL BLOCK DETAIL

DDS CORE

The direct digital synthesizer (DDS) block generates a reference signal (sine or cosine based on CFR1[16], the select DDS cosine output bit). The parameters of the reference signal (frequency, phase, and amplitude) are applied to the DDS at its frequency, phase offset, and amplitude control inputs, as shown in Figure 21.



Figure 21. DDS Block Diagram

The output frequency (f_{OUT}) of the AD9915 is controlled by the frequency tuning word (FTW) at the frequency control input to the DDS. The relationship among f_{OUT}, FTW, and f_{SYSCLK} is given by

$$f_{OUT} = \left(\frac{FTW}{2^{32}}\right) f_{SYSCLK} \quad (1)$$

where *FTW* is a 32-bit integer ranging in value from 0 to 2,147,483,647 ($2^{31} - 1$), which represents the lower half of the full 32-bit range. This range constitutes frequencies from dc to Nyquist (that is, ½ f_{SYSCLK}).

The FTW required to generate a desired value of f_{OUT} is found by solving Equation 1 for FTW, as given in Equation 2.

$$FTW = \text{round}\left(2^{32}\left(\frac{f_{OUT}}{f_{SYSCLK}}\right)\right) \quad (2)$$

where the round(*x*) function rounds the argument (the value of x) to the nearest integer. This is required because the FTW is constrained to be an integer value. For example, for f_{OUT} = 41 MHz and f_{SYSCLK} = 122.88 MHz, then FTW = 1,433,053,867 (0x556AAAAB).

Programming an FTW greater than 2^{31} produces an aliased image that appears at a frequency given by

$$f_{OUT} = \left(1 - \frac{FTW}{2^{32}}\right) f_{SYSCLK} \quad (\text{for FTW} \geq 2^{31})$$

The relative phase of the DDS signal can be digitally controlled by means of a 16-bit phase offset word (POW). The phase offset is applied prior to the angle-to-amplitude conversion block internal to the DDS core. The relative phase offset (Δθ) is given by

$$\Delta\theta = \begin{vmatrix} 2\pi\left(\frac{POW}{2^{14}}\right) \\ 360\left(\frac{POW}{2^{14}}\right) \end{vmatrix}$$

where the upper quantity is for the phase offset expressed as radian units and the lower quantity as degrees. To find the POW value necessary to develop an arbitrary Δθ, solve the previous equation for POW and round the result (in a manner similar to that described previously for finding an arbitrary FTW).

The relative amplitude of the DDS signal can be digitally scaled (relative to full scale) by means of a 12-bit amplitude scale factor (ASF). The amplitude scale value is applied at the output of the angle-to-amplitude conversion block internal to the DDS core. The amplitude scale is given by

$$Amplitude\ Scale = \begin{vmatrix} \frac{ASF}{2^{12}} \\ 20\log\left(\frac{ASF}{2^{12}}\right) \end{vmatrix} \quad (3)$$

where the upper quantity is amplitude expressed as a fraction of full scale and the lower quantity is expressed in decibels relative to full scale. To find the ASF value necessary for a particular scale factor, solve Equation 3 for ASF and round the result (in a manner similar to that described previously for finding an arbitrary FTW).

When the AD9915 is programmed to modulate any of the DDS signal control parameters, the maximum modulation sample rate is ¼ f_{SYSCLK}. This means that the modulation signal exhibits images at multiples of ¼ f_{SYSCLK}. The impact of these images must be considered when using the device as a modulator.

12-BIT DAC OUTPUT

The AD9915 incorporates an integrated 12-bit, current output DAC. The output current is delivered as a balanced signal using two outputs. The use of balanced outputs reduces the potential amount of common-mode noise present at the DAC output, offering the advantage of an increased signal-to-noise ratio. An external resistor (R_{SET}) connected between the DAC_RSET pin and AGND establishes the reference current. The recommended value of R_{SET} is 3.92 kΩ.

*NOTE: The DAC CAL in the DAC control register bit <24> must be manually set and then cleared after each power up and every time the REF CLK or internal system clock is changed. This will initiate an internal calibration routine to optimize the

setup and hold time for internal DAC timing. Failure to calibrate will degrade ac performance.

Attention should be paid to the load termination to keep the output voltage within the specified compliance range; voltages developed beyond this range cause excessive distortion and can damage the DAC output circuitry.

CLOCK INPUT (REF_CLK/$\overline{\text{REF\_CLK}}$)

REF_CLK/$\overline{\text{REF\_CLK}}$ Overview

The AD9915 supports a number of options for producing the internal SYSCLK signal (that is, the DAC sample clock) via the REF_CLK/$\overline{\text{REF\_CLK}}$ input pins. The REF_CLK input can be driven directly from a differential or single-ended source. There is also an internal phase-locked loop (PLL) multiplier that can be independently enabled. However, the PLL limits the SYSCLK signal between 2.4GHz to 2.5GHz operation. A block diagram of the REF_CLK functionality is shown in Figure 22. Figure 22 also shows how the CFR3 control bits are associated with specific functional blocks.



Figure 22. REF_CLK Block Diagram

The PLL enable bit is used to choose between the PLL path or the direct input path. When the direct input path is selected, the REF_CLK/$\overline{\text{REF\_CLK}}$ pins must be driven by an external signal source (single-ended or differential). Input frequencies up to 2.5 GHz are supported.

Direct Driven REF_CLK/$\overline{\text{REF\_CLK}}$

With a differential signal source, the REF_CLK/$\overline{\text{REF\_CLK}}$ pins are driven with complementary signals and ac-coupled with 0.1 µF capacitors. With a single-ended signal source, either a single-ended-to-differential conversion can be employed or the REF_CLK input can be driven single-ended directly. In either case, 0.1 µF capacitors are used to ac couple both REF_CLK/$\overline{\text{REF\_CLK}}$ pins to avoid disturbing the internal dc bias voltage of ~1.35 V. See Figure 23 for more details.

The REF_CLK/$\overline{\text{REF\_CLK}}$ input resistance is ~2.5 kΩ differential (~1.2 kΩ single-ended). Most signal sources have relatively low output impedances. The REF_CLK/$\overline{\text{REF\_CLK}}$ input resistance is relatively high; therefore, its effect on the termination impedance is negligible and can usually be chosen to be the same as the output impedance of the signal source. The bottom two examples in Figure 23 assume a signal source with a 50 Ω output impedance.



Figure 23. Direct Connection Diagram

Phase-Locked Loop (PLL) Multiplier

An internal phase-locked loop (PLL) provides the option to use a reference clock frequency that is significantly lower than the system clock frequency. The PLL supports a wide range of programmable frequency multiplication factors (8× to 255×) as well as a programmable charge pump current and external loop filter components (connected via the PLL_LOOP_FILTER pin). These features add an extra layer of flexibility to the PLL, allowing optimization of phase noise performance and flexibility in frequency plan development. The PLL is also equipped with a PLL_LOCK bit indicator.

The PLL output frequency range (f_{SYSCLK}) is constrained to the range of 2.GHz ≤ f_{SYSCLK} ≤ 2.5 GHz by the internal VCO.

PLL Charge Pump

The charge pump current (I_{CP}) is programmable to provide the user with additional flexibility to optimize the PLL performance. Table 4 lists the bit settings vs. the nominal charge pump current.

Table 4. PLL Charge Pump Current

I_{CP} Bits (CFR3[5:3])	Charge Pump Current, I_{CP} (µA)
000	125
001	250

010	375
011	500 (default)
100	625
101	750
110	875
111	1000

External PLL Loop Filter Components

The PLL_LOOP_FILTER pin provides a connection interface to attach the external loop filter components. The ability to use custom loop filter components gives the user more flexibility to optimize the PLL performance. The PLL and external loop filter components are shown in Figure 24.



Figure 24. REFCLK PLL External Loop Filter

In the prevailing literature, this configuration yields a third-order, Type II PLL. To calculate the loop filter component values, begin with the feedback divider value (N), the gain of the phase detector (K_D), and the gain of the VCO (K_V) based on the programmed VCO SEL bit settings (see Table 2 for K_V). The loop filter component values depend on the desired open-loop bandwidth (f_{OL}) and phase margin (φ), as follows:

$$R1 = \frac{\pi N f_{OL}}{K_D K_V}\left(1 + \frac{1}{\sin(\varphi)}\right) \quad (4)$$

$$C1 = \frac{K_D K_V \tan(\varphi)}{2N(\pi f_{OL})^2} \quad (5)$$

$$C2 = \frac{K_D K_V}{N(2\pi f_{OL})^2}\left(\frac{1-\sin(\varphi)}{\cos(\varphi)}\right) \quad (6)$$

where:
K_D is equal to the programmed value of I_{CP}.
K_V is taken from Table 2

Ensure that proper units are used for the variables in Equation 4 through Equation 6. I_{CP} must be in amps, not microamps (µA) as appears in Table 4; K_V must be in hertz per volts (Hz/V), not megahertz per volts (MHz/V) as listed in Table 2; the loop bandwidth (f_{OL}) must be in hertz (Hz); the phase margin (φ) must be in radians.

For example, suppose the PLL is programmed such that I_{CP} = 287 µA, K_V = 625 MHz/V, and N = 25. If the desired loop bandwidth and phase margin are 50 kHz and 45°, respectively, then the loop filter component values are R1 = 52.85 Ω, C1 = 145.4 nF, and C2 = 30.11 nF.

PLL LOCK INDICATION

When the PLL is in use, the PLL_LOCK bit provides an active high indication that the PLL has locked to the REFCLK input signal.

OUTPUT SHIFT KEYING (OSK)

The OSK function (see Figure 25) allows the user to control the output signal amplitude of the DDS. The amplitude data generated by the OSK block has priority over any other functional block that is programmed to deliver amplitude data to the DDS. Therefore, the OSK data source, when enabled, overrides all other amplitude data sources.



Figure 25. OSK Block Diagram

The operation of the OSK function is governed by two CFR1 register bits (OSK enable and external OSK enable), the external OSK pin, the profile pins, and the 12 bits of amplitude scale factor found in 1 of 8 profile registers. The profile pins are used to select the profile register containing the desired amplitude scale factor.

The primary control for the OSK block is the OSK Enable bit. When the OSK function is disabled (default), the OSK input controls and OSK pin are ignored.

The OSK pin functionality depends on the state of the external OSK control bit and OSK enable bit. When both bits are set to logic 1 and the OSK pin is Logic 0, the output amplitude is forced to 0; otherwise, if the OSK pin is Logic 1, the output amplitude is set by the amplitude scale factor value in 1 of 8 profile registers depending on the profile pin selection.

DIGITAL RAMP GENERATOR (DRG)

DRG Overview

To sweep phase, frequency, or amplitude from a defined start point to a defined endpoint, a completely digital, digital ramp generator is included in the AD9915. The DRG makes use of eight control register bits, three external pins, five 32-bit registers (see Figure 26).



Figure 26. Digital Ramp Block Diagram

The primary control for the DRG is the digital ramp enable bit. When disabled, the other DRG input controls are ignored and the internal clocks are shut down to conserve power.

The output of the DRG is a 32-bit unsigned data bus that can be routed to any one of the three DDS signal control parameters, as controlled by the two digital ramp destination bits in Control Function Register 2 according to Table 5. The 32-bit output bus is MSB-aligned with the 32-bit frequency parameter, the 14-bit phase parameter, or the 12-bit amplitude parameter, as defined by the destination bits. When the destination is phase or amplitude, the unused LSBs are ignored.

Table 5. Digital Ramp Destination

Digital Ramp Destination Bits (CFR2[21:20])	DDS Signal Control Parameter	Bits Assigned to DDS Parameter
00	Frequency	31:0
01	Phase	31:18
1x[1]	Amplitude	31:20

[1] x = Don't care.

The ramp characteristics of the DRG are fully programmable. This includes the upper and lower ramp limits, and independent control of the step size and step rate for both the positive and negative slope characteristics of the ramp. A detailed block diagram of the DRG is shown in Figure 27.

The direction of the ramping function is controlled by the DRCTL pin. A Logic 0 on this pin causes the DRG to ramp with a negative slope, whereas a Logic 1 causes the DRG to ramp with a positive slope.

The DRG also supports a hold feature controlled via the DRHOLD pin. When this pin is set to Logic 1, the DRG is stalled at its last state; otherwise, the DRG operates normally.

The DDS signal control parameters that are not the destination of the DRG are taken from the active profile.



Figure 27. Digital Ramp Generator Detail

DRG Slope Control

The core of the DRG is a 32-bit accumulator clocked by a programmable timer. The time base for the timer is the DDS clock, which operates at 1/24 f_{SYSCLK}. The timer establishes the interval between successive updates of the accumulator. The positive (+Δt) and negative (−Δt) slope step intervals are independently programmable as given by

$$+\Delta t = \frac{24P}{f_{SYSCLK}}$$

$$-\Delta t = \frac{24N}{f_{SYSCLK}}$$

where *P* and *N* are the two 16-bit values stored in the 32-bit digital ramp rate register and control the step interval. N defines the step interval of the negative slope portion of the ramp. P defines the step interval of the positive slope portion of the ramp.

The step size of the positive ($STEP_P$) and negative ($STEP_N$) slope portions of the ramp are 32-bit values programmed into the 64-bit digital ramp step size register. Program each of the step sizes as an unsigned integer (the hardware automatically interprets $STEP_N$ as a negative value). The relationship between the 32-bit step size values and actual units of frequency, phase, or amplitude depend on the digital ramp destination bits. Calculate the actual frequency, phase, or amplitude step size by substituting $STEP_N$ or $STEP_P$ for M in the following equations as required:

$$FrequencyStep = \left(\frac{M}{2^{32}}\right) f_{SYSCLK}$$

$$PhaseStep = \frac{\pi M}{2^{31}} \quad \text{(radians)}$$

$$PhaseStep = \frac{45M}{2^{29}} \quad \text{(degrees)}$$

$$AmplitudeStep = \left(\frac{M}{2^{32}}\right) I_{FS}$$

Note that the frequency units are the same as those used to represent f_{SYSCLK} (MHz, for example). The amplitude units are the same as those used to represent I_{FS}, the full-scale output current of the DAC (mA, for example).

The phase and amplitude step size equations yield the average step size. Although the step size accumulates with 32-bit precision, the phase or amplitude destination exhibits only 14 or 12 bits, respectively. Therefore, at the destination, the actual phase or amplitude step is the accumulated 32-bit value truncated to 14 or 12 bits, respectively.

As described previously, the step interval is controlled by a 16-bit programmable timer. There are three events that can cause this timer to be reloaded prior to its expiration. One event occurs when the digital ramp enable bit transitions from cleared to set, followed by an I/O update. A second event is a change of state in the DRCTL pin. The third event is enabled using the load LRR @ I/O update bit (see the **Error! Not a valid bookmark self-reference.** section for details).

DRG Limit Control

The ramp accumulator is followed by limit control logic that enforces an upper and lower boundary on the output of the ramp generator. Under no circumstances does the output of the DRG exceed the programmed limit values while the DRG is enabled. The limits are set through the 64-bit digital ramp limit register. Note that the upper limit value must be greater than the lower limit value to ensure normal operation.

DRG Accumulator Clear

The ramp accumulator can be cleared (that is, reset to 0) under program control. When the ramp accumulator is cleared, it forces

the DRG output to the lower limit programmed into the digital ramp limit register.

With the limit control block embedded in the feedback path of the accumulator, resetting the accumulator is equivalent to presetting it to the lower limit value.

Normal Ramp Generation

Normal ramp generation implies that both no-dwell bits are cleared (see the No-Dwell Ramp Generation section for details). In Figure 28, a sample ramp waveform is depicted with the required control signals. The top trace is the DRG output. The next trace down is the status of the DROVER output pin (assuming that the DROVER pin active bit is set). The remaining traces are control bits and control pins. The pertinent ramp parameters are also identified (upper and lower limits plus step size and Δt for the positive and negative slopes). Along the bottom, circled numbers identify specific events. These events are referred to by number (Event 1 and so on) in the following paragraphs.

In this particular example, the positive and negative slopes of the ramp are different to demonstrate the flexibility of the DRG. The parameters of both slopes can be programmed to make the positive and negative slopes the same.



Figure 28. Normal Ramp Generation

Event 1—The digital ramp enable bit is set, which has no effect on the DRG output because the bit is not effective until an I/O update.

Event 2—An I/O update registers the enable bit. If DRCTL = 1 is in effect at this time (the gray portion of the DRCTL trace), then the DRG output immediately begins a positive slope (the gray portion of the DRG output trace). Otherwise, if DRCTL = 0, the DRG output is initialized to the lower limit.

Event 3—DRCTL transitions to a Logic 1 to initiate a positive slope at the DRG output. In this example, the DRCTL pin is held long enough to cause the DRG to reach its programmed upper limit. The DRG remains at the upper limit until the ramp accumulator is cleared, DRCTL = 0, or the upper limit is reprogrammed to a higher value. In the last case, the DRG immediately resumes its previous positive slope profile.

Event 4—DRCTL transitions to a Logic 0 to initiate a negative slope at the DRG output. In this example, the DRCTL pin is held long enough to cause the DRG to reach its programmed lower limit. The DRG remains at the lower limit until DRCTL = 1, or until the lower limit is reprogrammed to a lower value. In the latter case, the DRG immediately resumes its previous negative slope profile.

Event 5—DRCTL transitions to a Logic 1 for the second time, initiating a second positive slope.

Event 6—The positive slope profile is interrupted by DRHOLD transitioning to a Logic 1. This stalls the ramp accumulator and freezes the DRG output at its last value.

Event 7—DRHOLD transitions to a Logic 0, releasing the ramp accumulator and reinstating the previous positive slope profile.

Event 8—The clear digital ramp accumulator bit is set, which has no effect on the DRG because the bit is not effective until an I/O update is issued.

Event 9—An I/O update registers that the clear digital ramp accumulator bit is set, resetting the ramp accumulator and forcing the DRG output to the programmed lower limit. The

DRG output remains at the lower limit until the clear condition is removed.

Event 10—The clear digital ramp accumulator bit is cleared, which has no effect on the DRG output because the bit is not effective until an I/O update is issued.

Event 11—An I/O update registers that the clear digital ramp accumulator bit is cleared, releasing the ramp accumulator, and the previous positive slope profile restarts.

Event 12—The autoclear digital ramp accumulator bit is set, which has no effect on the DRG output because the bit is not effective until an I/O update is issued.

Event 13—An I/O update registers that the autoclear digital ramp accumulator bit is set, resetting the ramp accumulator. However, with an automatic clear, the ramp accumulator is only held reset for a single DDS clock cycle. This forces the DRG output to the lower limit, but the ramp accumulator is immediately made available for normal operation. In this example, the DRCTL pin remains a Logic 1; therefore, the DRG output restarts the previous positive ramp profile.

No-Dwell Ramp Generation

The two no-dwell bits in Control Function Register 2 add to the flexibility of the DRG capabilities. During normal ramp generation, when the DRG output reaches the programmed upper or lower limit, it simply remains at the limit until the operating parameters dictate otherwise. However, during no-dwell operation, the DRG output does not necessarily remain at the limit. For example, if the digital ramp no-dwell high bit is set when the DRG reaches the upper limit, it automatically (and immediately) snaps to the lower limit (that is, it does not ramp back to the lower limit; it jumps to the lower limit). Likewise, when the digital ramp no-dwell low bit is set, and the DRG reaches the lower limit, it automatically (and immediately) snaps to the upper limit.

During no-dwell operation, the DRCTL pin is monitored for state transitions only; that is, the static logic level is immaterial.

During no-dwell high operation, a positive transition of the DRCTL pin initiates a positive slope ramp, which continues uninterrupted (regardless of any further activity on the DRCTL pin) until the upper limit is reached.

During no-dwell low operation, a negative transition of the DRCTL pin initiates a negative slope ramp, which continues uninterrupted (regardless of any further activity on the DRCTL pin) until the lower limit is reached.

Setting both no-dwell bits invokes a continuous ramping mode of operation; that is, the DRG output automatically oscillates between the two limits using the programmed slope parameters. Furthermore, the function of the DRCTL pin is slightly different. Instead of controlling the initiation of the ramp sequence, it only serves to change the direction of the ramp; that is, if the DRG output is in the midst of a positive slope and the DRCTL pin transitions from Logic 1 to Logic 0, then the DRG immediately switches to the negative slope parameters and resumes oscillation between the limits. Likewise, if the DRG output is in the midst of a negative slope and the DRCTL pin transitions from Logic 0 to Logic 1, the DRG immediately switches to the positive slope parameters and resumes oscillation between the limits.

When both no-dwell bits are set, the DROVER signal produces a positive pulse (two cycles of the DDS clock) each time the DRG output reaches either of the programmed limits (assuming that the DROVER pin active bit is set).

A no-dwell high DRG output waveform is shown in Figure 29. The waveform diagram assumes that the digital ramp no-dwell high bit is set and has been registered by an I/O update. The status of the DROVER pin is also shown with the assumption that the DROVER pin active bit has been set.



Figure 29. No-Dwell High Ramp Generation

The circled numbers in Figure 29 indicate specific events, which are explained as follows:

Event 1—Indicates the instant that an I/O update registers that the digital ramp enable bit has been set.

Event 2—DRCTL transitions to a Logic 1, initiating a positive slope at the DRG output.

Event 3—DRCTL transition to a Logic 0, which has no effect on the DRG output.

Event 4—Because the digital ramp no-dwell high bit is set, the moment that the DRG output reaches the upper limit, it immediately switches to the lower limit, where it remains until the next Logic 0 to Logic 1 transition of DRCTL.

Event 5—DRCTL transitions from Logic 0 to Logic 1, which restarts a positive slope ramp.

Event 6 and Event 7—DRCTL transitions are ignored until the DRG output reaches the programmed upper limit.

Event 8—Because the digital ramp no-dwell high bit is set, the moment that the DRG output reaches the upper limit, it immediately switches to the lower limit, where it remains until the next Logic 0 to Logic 1 transition of DRCTL.

Operation with the digital ramp no-dwell low bit set (instead of the digital ramp no-dwell high bit) is similar, except that the DRG output ramps in the negative direction on a Logic 1 to Logic 0 transition of DRCTL and jumps to the upper limit upon reaching the lower limit.

DROVER Pin

The DROVER pin provides an external signal to indicate the status of the DRG. Specifically, when the DRG output is at either of the programmed limits, the DROVER pin is Logic 1; otherwise, it is Logic 0. In the special case of both no-dwell bits set, the DROVER pin pulses positive for two DDS clock cycles each time the DRG output reaches either of the programmed limits.

Frequency Jumping Capability in DRG Mode

Another feature of AD9915 allows the user to skip a pre-defined range of frequencies during a normal sweep. Control bit in CFR2<14> will enable this functionality. When this bit is set, the sweeping logic will monitor the instantaneous frequency, when it hits the frequency point defined in Frequency Jump Register 1, on the next accumulation cycle, instead of accumulating a DELTA tuning word as in normal sweeping, it will skip directly to the frequency value set in the Frequency Jump Register 2.

A second frequency jump can also be allowed if Frequency Skip Register 2 is reprogrammed before the sweeping is complete. See the following frequency verses time plot to show how this feature works.

Rules apply when this feature is enabled.

(1) The frequency jump points must lie between the lower limit and upper limit of the sweep.
(2) The jump range has to be limited to the amount that after the jump the frequency doesn't exceed the limit.
(3) Frequency Skip Register 2 has to be larger than Frequency Skip Register 1



POWER-DOWN CONTROL

The AD9915 offers the ability to independently power down three specific sections of the device. Power-down functionality applies to the following:

- Digital core
- DAC
- Input REFCLK clock circuitry

A power-down of the digital core disables the ability to update the serial /parallel I/O port. However, the digital power-down bit can still be cleared to prevent the possibility of a non-recoverable state.

Software power-down is controlled via three independent power-down bits in Control Function Register 1 (CFR1). Software control requires that the EXT_PWR_DWN pin be forced to a Logic 0 state. In this case, setting the desired power-down bits (via the serial I/O port) powers down the associated functional block, whereas clearing the bits restores the function.

Alternatively, all three functions can be simultaneously powered down via external hardware control through the EXT_PWR_DWN pin. When this pin is forced to Logic 1, all four circuit blocks are powered down regardless of the state of the power-down bits; that is, the independent power-down bits in CFR1 are ignored and overridden when EXT_PWR_DWN is Logic 1.

Based on the state of the external power-down control bit, the EXT_PWR_DWN pin produces either a full power-down or a fast recovery power-down. The fast recovery power-down mode maintains power to the DAC bias circuitry and the PLL, VCO, and input clock circuitry. Although the fast recovery power-down does not conserve as much power as the full power-down, it allows the device to awaken very quickly from the power-down state.

PROGRAMMING AND FUNCTION PINS

The AD9915 is equipped with a 32-bit parallel port. The 32-bit port is for programming the internal registers of the device in either a serial or parallel mode as well as allow for direct modulation control of Frequency, Phase and Amplitude. The state of the external function pins (F0 to F3) determine how the 32-bit parallel port is configured. Pins 28 to 31 on the AD9915 are the function pins. Refer to table 4 below for possible configurations.

Table 4.

Function pins	Mode Description	32-bit Parallel Port pin assignment			
Pins 31-28		Pins 68-72, 75-77	Pins 78-81, 87, 88, 1-2	Pins 3-5, 8-12	Pins 13-15, 18-22
Bits <3:0>		**Bits <31:24>**	**Bits <23:16>**	**Bits <15:8>**	**Bits<7:0>**
0000	Parallel programming mode	Data <15:8> (Optional)	Data <7:0>	Address <7:0>	Used to control writes, reads, and 8 or 16 data word. See Parallel Programming section for details.
0001	Serial Programming mode	Not Used	Not Used	Not used	Used to control SCLK, SDIO, SDO, CSB and SYNC_IO. See Serial Programming section for details.
0010	Direct tuning word control 32-bits; 16-bit (lsb) FTW control	FTW<31:24>	FTW<23:16>	FTW<15:8>	FTW<7:0>
0011	Direct tuning word control 32-bits; 16-bit (msb) FTW control	FTW<15:8>	FTW<7:0>	FTW<31:24>	FTW<23:16>
0100	Direct phase and amplitude control; 16 bit direct amplitude control	POW<15:8>	POW<7:0>	AMP<15:8>	AMP<7:0>
0101	Direct phase and amplitude control; 16 bit direct POW control	AMP<15:8>	AMP<7:0>	POW<15:8>	POW<7:0>
0110	Partial FTW (msb) and Amplitude control (msb)	FTW<31:24>	FTW<23:16>	FTW<15:8>	AMP<15:8>
0111	Partial FTW (msb) and Phase (msb) control	FTW<31:24>	FTW<23:16>	FTW<15:8>	POW<15:8>
1000	Partial FTW (msb) and Amplitude control (lsb)	FTW<31:24>	FTW<23:16>	FTW<15:8>	AMP<7:0>
1001	Partial FTW (msb) and Phase (lsb) control	FTW<31:24>	FTW<23:16>	FTW<15:8>	POW<7:0>
1010	Partial FTW (lsb) and Amplitude control (lsb)	FTW<23:16>	FTW<15:8>	FTW<7:0>	AMP<15:8>
1011	Partial FTW (lsb) and Phase (lsb) control	FTW<23:16>	FTW<15:8>	FTW<7:0>	POW<15:8>

1100	Partial FTW (lsb) and Amplitude control (lsb)	FTW<23:16>	FTW<15:8>	FTW<7:0>	AMP<7:0>
1101	Partial FTW (lsb) and Phase (lsb) control	FTW<23:16>	FTW<15:8>	FTW<7:0>	POW<7:0>
1110		Not Used	Not Used	Not Used	Not Used
1111		Not Used	Not Used	Not Used	Not Used

SERIAL PROGRAMMING

To enable SPI operations set pin 28 to logic high and pins 29-31 logic low. To program the AD9915 with a parallel interface see the Parallel Programming section.

CONTROL INTERFACE—SERIAL I/O

The AD9915 serial port is a flexible, synchronous serial communications port allowing easy interface to many industry-standard microcontrollers and microprocessors. The serial I/O is compatible with most synchronous transfer formats.

The interface allows read/write access to all registers that configure the AD9915. MSB-first or LSB-first transfer formats are supported. In addition, the serial interface port can be configured as a single pin input/output (SDIO) allowing a 2-wire interface, or it can be configured as two unidirectional pins for input/output (SDIO/SDO) enabling a 3-wire interface. Two optional pins (I/O_SYNC and $\overline{CS}$) enable greater flexibility for designing systems with the AD9915.

Table 5 . Serial I/O Pin Description

Pin Number	Mnemonic	Serial I/O Description
18	D4/SYNC_IO	SYNC_IO
19	D3/SDO	SDO
20	D2/SDIO/WRB	SDIO
21	D1/SCLK/RDB	SCLK
22	D0//$\overline{CS}$/PWD	$\overline{CS}$—Chip Select.

GENERAL SERIAL I/O OPERATION

There are two phases to a serial communications cycle. The first is the instruction phase to write the instruction byte into the AD9915S. The instruction byte contains the address of the register to be accessed (see the **Error! Not a valid bookmark self-reference.** section) and defines whether the upcoming data transfer is a write or read operation.

For a write cycle, Phase 2 represents the data transfer between the serial port controller to the serial port buffer. The number of bytes transferred is a function of the register being accessed. For example, when accessing the Control Function Register 2 (Address 0x01), Phase 2 requires that four bytes be transferred. Each bit of data is registered on each corresponding rising edge of SCLK. The serial port controller expects that all bytes of the register be accessed; otherwise, the serial port controller is put out of sequence for the next communication cycle. However, one way to write fewer bytes than required is to use the SYNC I/Opin feature. The SYNC I/Opin function can be used to abort an I/O operation and reset the pointer of the serial port controller. After an SYNC I/O, the next byte is the instruction byte. Note that every completed byte written prior to an SYNC I/O is preserved in the serial port buffer. Partial bytes written are not preserved. At the completion of any communication cycle, the AD9915 serial port controller expects the next eight rising SCLK edges to be the instruction byte for the next communication cycle.

After a write cycle, the programmed data resides in the serial port buffer and is inactive. I/O_UPDATE transfers data from the serial port buffer to active registers. The I/O update can be sent either after each communication cycle or when all serial operations are complete. In addition, a change in profile pins can initiate an I/O update.

For a read cycle, Phase 2 is the same as the write cycle with the following differences: data is read from the active registers, not the serial port buffer, and data is driven out on the falling edge of SCLK.

Note that to read back any profile register (0x0B to 0x1A), the three external profile pins must be used. For example, if the profile register is Profile 5 (0x15), then the PROFILE[0:2] pins must equal 101.This is not required to write to profile registers.

INSTRUCTION BYTE

The instruction byte contains the following information as shown in the instruction byte information bit map.

Instruction Byte Information Bit Map

MSB							LSB
D7	D6	D5	D4	D3	D2	D1	D0
R/$\overline{W}$	X	A5	A4	A3	A2	A1	A0

R/$\overline{W}$—Bit 7 of the instruction byte determines whether a read or write data transfer occurs after the instruction byte write. Logic 1 indicates a read operation. Cleared indicates a write operation.

X—Bit 6 of the instruction byte is don't care.

A5,A4, A3, A2, A1, A0—Bit 5, Bit 4, Bit 3, Bit 2, Bit 1, and Bit 0 of the instruction byte determine which register is accessed during the data transfer portion of the communications cycle.

SERIAL I/O PORT PIN DESCRIPTIONS

SCLK—Serial Clock

The serial clock pin is used to synchronize data to and from the AD9915 and to run the internal state machines.

$\overline{CS}$—Chip Select Bar

$\overline{CS}$ is an active low input that allows more than one device on the same serial communications line. The SDO and SDIO pins

go to a high impedance state when this input is high. If driven high during any communications cycle, that cycle is suspended until $\overline{CS}$ is reactivated low. Chip select ($\overline{CS}$) can be tied low in systems that maintain control of SCLK.

SDIO—Serial Data Input/Output

Data is always written into the AD9915 on this pin. However, this pin can be used as a bidirectional data line. Bit 1 of CFR1 Register Address 0x00 controls the configuration of this pin. The default is cleared, which configures the SDIO pin as bidirectional.

SDO—Serial Data Out

Data is read from this pin for protocols that use separate lines for transmitting and receiving data. When the AD9915 operates in single bidirectional I/O mode, this pin does not output data and is set to a high impedance state. SYNC I/O—Input/Output Reset

SYNC_IO

SYNC _IO synchronizes the I/O port state machines without affecting the contents of the addressable registers. An active high input on the SYNC I/O pin causes the current communication cycle to abort. After SYNC I/O returns low (Logic 0), another communication cycle can begin, starting with the instruction byte write.

I/O_UPDATE—Input/Output Update

The I/O_UPDATE initiates the transfer of written data from the serial or parallel I/O port buffer to active registers. I/O_UPDATE is active on the rising edge, and its pulse width must be greater than one SYNC_CLK period.

SERIAL I/O TIMING DIAGRAMS

Figure 30 through Figure 33 provide basic examples of the timing relationships between the various control signals of the serial I/O port. Most of the bits in the register map are not transferred to their internal destinations until assertion of an I/O update, which is not included in the timing diagrams that follow.

MSB/LSB TRANSFERS

The AD9915 serial port can support both most significant bit (MSB) first or least significant bit (LSB) first data formats. This functionality is controlled by Bit 0 in Control Function Register 1 (0x00). The default format is MSB first. If LSB first is active, all data, including the instruction byte, must follow LSB-first convention. Note that the highest number found in the bit range column for each register is the MSB, and the lowest number is the LSB for that register (see the **Error! Not a valid bookmark self-reference.** section).



Figure 30. Serial Port Write Timing, Clock Stall Low



Figure 31. 3-Wire Serial Port Read Timing, Clock Stall Low



Figure 32. Serial Port Write Timing, Clock Stall High



Figure 33. 2-Wire Serial Port Read Timing, Clock Stall High

PARALLEL PROGRAMMING

The state of the external function pins (F0 to F3) determine the type of interface used by the AD9915. Pins 28 to 31 are dedicated function pins. To enable the parallel mode interface set pins 28-31 to logic low.

Parallel programming consists of eight address lines and either eight or sixteen bidirectional data lines for read/write operations. The logic state on pin 22 determines the width of the data lines used. A logic low on pin 22 sets the data width to 8 bits and logic high sets the data width to 16-bits. In addition, parallel mode has dedicated write/read control inputs. If 16-bit mode is used the upper byte <15:8> goes to the addressed register and the lower byte <7:0> goes to the adjacent lower address.

Parallel I/O operation allows write access to each byte of any register in a single I/O operation. Read back capability for each register is included to ease designing with the AD9915.



SPECIFICATION	VALUE	DESCRIPTION
t_{ADV}	ns	ADDRESS TO DATA VALID TIME (MAXIMUM)
t_{AHD}	ns	ADDRESS HOLD TIME TO RD SIGNAL INACTIVE (MINIMUM)
t_{RDLOV}	ns	RD LOW TO OUTPUT VALID (MAXIMUM)
t_{RDHOZ}	ns	RD HIGH TO DATA THREE-STATE (MAXIMUM)

Figure 34. Parallel Port Read Timing Diagram



SPECIFICATION	VALUE	DESCRIPTION
t_{ASU}	ns	ADDRESS SETUP TIME TO WR SIGNAL ACTIVE
t_{DSU}	ns	DATA SETUP TIME TO WR SIGNAL ACTIVE
t_{ADH}	ns	ADDRESS HOLD TIME TO WR SIGNAL INACTIVE
t_{DHD}	ns	DATA HOLD TIME TO WR SIGNAL INACTIVE
t_{WRLOW}	ns	WR SIGNAL MINIMUM LOW TIME
t_{WRHIGH}	ns	WR SIGNAL MINIMUM HIGH TIME
t_{WR}	ns	MINIMUM WRITE TIME

Figure 35. Parallel Port Write Timing Diagram

REGISTER MAP AND BIT DESCRIPTIONS

Table. Register Map

Register Name (Serial Address)	Bit Range (Parallel Address)	Bit 7 (MSB)	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0 (LSB)	Default Value[1] (Hex)
CFR1—Control Function Register 1 (0x00)	7:0 (0x00)	Digital Power Down	DAC Power Down	REFCLK Power Down	Open	External Power Down	Open	SDIO Input only	LSB First Mode	0x08
	15:8 (0x01)	Load LRR @ I/O Update	Auto Clear DRG	Auto Clear Phase Accumu-lator	Clear DRG	Clear Phase Accumu-lator	Open	External OSK Enable	OSK Enable	0x00
	23:16 (0x02)	Open						Relieve Data Port IO Sync	Enable Sine Output	0x01
	31:24 (0x03)	Open							PLL Cal Enable	0x00
CFR2—Control Function Register 2 (0x01)	7:0 (0x04)	Open								0x00
	15:8 (0x05)	Matched Latency Enable	Frequency Jump Enable	DRG Over Output Enable	Open	SYNC_CLK Enable	SYNC_CLK Invert	MCS Onetime Shot Enable	SYNC_OUT Enable	0x09
	23:16 (0x06)	Profile Mode Enable	Data Port Mode Enable	DRG Destination		DRG Enable	No Dwell High	No Dwell Low	Program Modulus Enable	0x00
	31:24 (0x07)	Open								0x00
CFR3—Control Function Register 3 (0x02)	7:0 (0x08)	Open	Manual ICP Selection	ICP (2:0)			Lock Detect Enable	Minimum LDW (1:0)		0x1C
	15:8 (0x09)	Feedback Divider NCNT (7:0)								0x19
	23:16 (0x0A)a	Open	Input Divider Reset	Input Divider RDIV (1:0)		Doubler Enable	PLL Enable	PLL Ref Enable	Doubler Clock Edge	0x00
	31:24 (0x0B)	Open								0x00
DAC—Control Register (0x03)	7:0 (0x0C)	Open	DAC Clock FF Bias (1:0)		STMTSRDIV2		Open			0x20
	15:8 (0x0D)	MCS Bandgap Trim (2:0)			DC:LK Phase 0 Select		Decode Logic Bandgap Trim (2:0)			0x31
	23:16 (0x0E)	Open	DIG CLK Polarity	DDSCLK Polarity	Open	RMX FF Bias (1:0)		MCS FF Bias (1:0)		0x05
	31:24 (0x)F)	Open					Free Running Divider Power Down	Cal Clock Power Down	***DAC CAL Enable**	0x00
Digital Ramp Lower Limit Register (0x04)	7:0 (0x10)	DRG Lower limit[7:0]								0x00
	15:8 (0x11)	DRG Lower limit[15:8]								0x00
	23:16	DRG Lower limit[23:16]								0x00

Register Name (Serial Address)	Bit Range (Parallel Address)	Bit 7 (MSB)	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0 (LSB)	Default Value[1] (Hex)
	(0x12)									
	31:24 (0x13)	DRG Lower limit[31:24]								0x00
Digital Ramp Upper Limit Register (0x05)	7:0 (0x14)	DRG Upper limit[7:0]								0x01
	15:8 (0x15)	DRG Upper limit[15:8]								0x01
	23:16 (0x16)	DRG Upper limit[23:16]								0x01
	31:24 (0x17)	DRG Upper limit[31:24]								0x01
Rising Digital Ramp Step Size Register (0x06)	7:0 (0x18)	Rising DRG Step Size[7:0]								0x01
	15:8 (0x19)	Rising DRG Step Size[15:8]								0x01
	23:16 (0x1A)	Rising DRG Step Size[23:16]								0x01
	31:24 (0x1B)	Rising DRG Step Size[31:24]								0x01
Falling Digital Ramp Step Size Register (0x07)	7:0 (0x1C)	Falling DRG Step Size[7:0]								0x00
	15:8 (0x1D)	Falling DRG Step Size[15:8]								0x00
	23:16 (0x1E)	Falling DRG Step Size[23:16]								0x00
	31:24 (0x1F)	Falling DRG Step Size[31:24]								0x00
Digital Ramp Rate Register (0x08)	7:0 (0x20)	Rising DRG ramp rate [7:0]								0x01
	15:8 (0x21)	Rising DRG ramp rate[15:8]								0x01
	23:16 (0x22)	Falling DRG ramp rate[7:0]								0x00
	31:24 (0x23)	Falling DRG ramp rate[15:8]								0x00
Frequency Skip Register 1 (0x09)	7:0 (0x24)	Frequency Jump Point [7:0]								0x00
	15:8 (0x25)	Frequency Jump Point [15:8]								0x00
	23:16 (0x26)	Frequency Jump Point [23:16]								0x00
	31:24 (0x27)	Frequency Jump Point [31:24]								0x00
Frequency Skip Register 2 (0x0A)	7:0 (0x28)	Frequency Jump Amount [7:0]								0x00
	15:8 (0x29)	Frequency Jump Amount [15:8]								0x00
	23:16 (0x2A)	Frequency Jump Amount [23:16]								0x00
	31:24 (0x2B)	Frequency Jump Amount [31:24]								0x00

Register Name (Serial Address)	Bit Range (Parallel Address)	Bit 7 (MSB)	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0 (LSB)	Default Value[1] (Hex)	
Profile 0 Frequency Tuning Word 0 Register (0x0B)	7:0 (0x2C)	Frequency Tuning Word 0 [7:0]								0x00	P0
	15:8 (0x2D)	Frequency Tuning Word 0 [15:8]								0x00	P0
	23:16 (0x2E)	Frequency Tuning Word 0 [23:16]								0x00	P0
	31:24 (0x2F)	Frequency Tuning Word 0 [31:24]								0x00	P0
Profile 0 Phase/Amplitude Register (0x0C)	7:0 (0x30)	Phase Offset Word 0 [7:0]								0x00	P0
	15:8 (0x31)	Phase Offset Word 0 [15:8]								0x00	P0
	23:16 (0x32)	Amplitude Scale Factor 0 [7:0]								0x00	P0
	31:24 (0x33)	Open				Amplitude Scale Factor 0 [11:8]				0x00	P0
Profile 1 Frequency Tuning Word 1 Register (0x0D)	7:0 (0x34)	Frequency Tuning Word 1 [7:0]								0x00	P1
	15:8 (0x35)	Frequency Tuning Word 1 [15:8]								0x00	P1
	23:16 (0x36)	Frequency Tuning Word 1 [23:16]								0x00	P1
	31:24 (0x37)	Frequency Tuning Word 1 [31:24]								0x00	P1
Profile 1 Phase/Amplitude Register (0x0E)	7:0 (0x38)	Phase Offset Word 1 [7:0]								0x00	P1
	15:8 (0x39)	Phase Offset Word 1 [15:8]								0x00	P1
	23:16 (0x3A)	Amplitude Scale Factor 1 [7:0]								0x00	P1
	31:24 (0x3B)	Open				Amplitude Scale Factor 1 [11:8]				0x00	P1
Profile 2 Frequency Tuning Word 2 Register (0x0F)	7:0 (0x3C)	Frequency Tuning Word 2 [7:0]								0x00	P2
	15:8 (0x3D)	Frequency Tuning Word 2 [15:8]								0x00	P2
	23:16 (0x3E)	Frequency Tuning Word 2 [23:16]								0x00	P2
	31:24 (0x3F)	Frequency Tuning Word 2 [31:24]								0x00	P2
Profile 2 Phase/Amplitude	7:0 (0x40)	Phase Offset Word 2 [7:0]								0x00	P

Register Name (Serial Address)	Bit Range (Parallel Address)	Bit 7 (MSB)	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0 (LSB)	Default Value[1] (Hex)	
Register											2
(0x10)	15:8 (0x41)	Phase Offset Word 2 [15:8]								0x00	P 2
	23:16 (0x42)	Amplitude Scale Factor 2 [7:0]								0x00	P 2
	31:24 (0x43)	Open				Amplitude Scale Factor 2 [11:8]				0x00	P 2
Profile 3 Frequency Tuning Word 3 Register	7:0 (0x44)	Frequency Tuning Word 3 [7:0]								0x00	P 3
(0x11)	15:8 (0x45)	Frequency Tuning Word 3 [15:8]								0x00	P 3
	23:16 (0x46)	Frequency Tuning Word 3 [23:16]								0x00	P 3
	31:24 (0x47)	Frequency Tuning Word 3 [31:24]								0x00	P 3
Profile 3 Phase/Amplitude Register	7:0 (0x48)	Phase Offset Word 3 [7:0]								0x00	P 3
(0x12)	15:8 (0x49)	Phase Offset Word 3 [15:8]								0x00	P 3
	23:16 (0x4A)	Amplitude Scale Factor 3 [7:0]								0x00	P 3
	31:24 (0x4B)	Open				Amplitude Scale Factor 3 [11:8]				0x00	P 3
Profile 4 Frequency Tuning Word 4 Register	7:0 (0x4C)	Frequency Tuning Word 4 [7:0]								0x00	P 4
(0x13)	15:8 (0x4D)	Frequency Tuning Word 4 [15:8]								0x00	P 4
	23:16 (0x4E)	Frequency Tuning Word 4 [23:16]								0x00	P 4
	31:24 (0x4F)	Frequency Tuning Word 4 [31:24]								0x00	P 4
Profile 4 Phase/Amplitude Register	7:0 (0x50)	Phase Offset Word 4 [7:0]								0x00	P 4
(0x14)	15:8 (0x51)	Phase Offset Word 4 [15:8]								0x00	P 4
	23:16 (0x52)	Amplitude Scale Factor 4 [7:0]								0x00	P 4
	31:24 (0x53)	Open				Amplitude Scale Factor 4 [11:8]				0x00	P 4
Profile 5 Frequency Tuning Word 5 Register	7:0 (0x54)	Frequency Tuning Word 5 [7:0]								0x00	P 5
	15:8	Frequency Tuning Word 5 [15:8]								0x00	P

Register Name (Serial Address)	Bit Range (Parallel Address)	Bit 7 (MSB)	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0 (LSB)	Default Value[1] (Hex)	
(0x15)	(0x55)										5
	23:16 (0x56)	Frequency Tuning Word 5 [23:16]								0x00	P 5
	31:24 (0x57)	Frequency Tuning Word 5 [31:24]								0x00	P 5
Profile 5 Phase/Amplitude Register (0x16)	7:0 (0x58)	Phase Offset Word 5 [7:0]								0x00	P 5
	15:8 (0x59)	Phase Offset Word 5 [15:8]								0x00	P 5
	23:16 (0x5A)	Amplitude Scale Factor 5 [7:0]								0x00	P 5
	31:24 (0x5B)	Open				Amplitude Scale Factor 5 [11:8]				0x00	P 5
Profile 6 Frequency Tuning Word 6 Register (0x17)	7:0 (0x5C)	Frequency Tuning Word 6 [7:0]								0x00	P 6
	15:8 (0x5D)	Frequency Tuning Word 6 [15:8]								0x00	P 6
	23:16 (0x5E)	Frequency Tuning Word 6 [23:16]								0x00	P 6
	31:24 (0x5F)	Frequency Tuning Word 6 [31:24]								0x00	P 6
Profile 6 Phase/Amplitude Register (0x18)	7:0 (0x60)	Phase Offset Word 6 [7:0]								0x00	P 6
	15:8 (0x61)	Phase Offset Word 6 [15:8]								0x00	P 6
	23:16 (0x62)	Amplitude Scale Factor 6 [7:0]								0x00	P 6
	31:24 (0x63)	Open				Amplitude Scale Factor 6 [11:8]				0x00	P 6
Profile 7 Frequency Tuning Word 7 Register (0x19)	7:0 (0x64)	Frequency Tuning Word 7 [7:0]								0x00	P 7
	15:8 (0x65)	Frequency Tuning Word 7 [15:8]								0x00	P 7
	23:16 (0x66)	Frequency Tuning Word 7 [23:16]								0x00	P 7
	31:24 (0x67)	Frequency Tuning Word 7 [31:24]								0x00	P 7
Profile 7 Phase/Amplitude Register (0x1A)	7:0 (0x68)	Phase Offset Word 7 [7:0]								0x00	P 7
	15:8 (0x69)	Phase Offset Word 7 [15:8]								0x00	P 7
	23:16	Amplitude Scale Factor 7 [7:0]								0x00	P

Register Name (Serial Address)	Bit Range (Parallel Address)	Bit 7 (MSB)	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0 (LSB)	Default Value[1] (Hex)	
	(0x6A)										7
	31:24 (0x6B)	Open				Amplitude Scale Factor 7 [11:8]				0x00	P 7
USR 0 0x1B	7:0 (0x6C)	RSYNC	CALWOSYNC	SYNC OUT ADJ [2;0]			SYNC IN ADJ [2:0]			0x00	
	15:8 (0x6D)	OPEN [2:0]			TDAC REF [1:0]		SYNC GATE2 BP	SYNC GATE BP	SRC DLL ENABLE	0x08	
	23:16 (0x6E)	OPEN	CAL RST	FORCE DELAY	DELAY [4:0]					0x00	
	31:24 (0x6F)	PID [1:0]		DIE [2:0]			OPEN	OPEN	PLL LOCK	READ ONLY	

**NOTE: The DAC CAL bit must be manually set and then cleared after each power up and every time the REF CLK or internal system clock is changed. This will initiate an internal calibration routine to optimize the setup and hold time for internal DAC timing. Failure to calibrate will degrade ac performance.*

Control Function Register 1 (CFR1)—Address 0x00

Four bytes are assigned to this register.

Table. Bit Description for CFR1

Bit(s)	Mnemonic	Description
31:25	Open	
24	PLL Cal Enable	
23:18	Open	
17	Relieve Data Port IO SYNC	0 = the data port needs an io_update to activate the FTW/POW/AMP. 1 = the data port continuously samples the input pins using dp_clk and multiplexes the value into FTW/POW/AMP according to the DP_CTL configuration.
16	Enable Cosine output	0 = Sine output of the DDS is selected (default). 1 = Cosine output of the DDS is selected.
15	Load LRR @ I/O update	Ineffective unless CFR2[19] = 1. 0 = normal operation of the digital ramp timer (default). 1 = digital ramp timer loaded any time I/O_UPDATE is asserted or a PROFILE[2:0] change occurs.
14	Auto Clear DRG	0 = Normal operation of the DRG accumulator (default). 1 = The ramp accumulator is reset for one cycle of the DDS clock after which the accumulator automatically resumes normal operation. As long as this bit remains set, the ramp accumulator is momentarily reset each time an I/O_UPDATE is asserted or a PROFILE[2:0] change occurs. This bit is synchronized with either an I/O _UPDATE or a PROFILE[2:0] change and the next rising edge of SYNC_CLK.
13	Auto Clear Phase Accumulator	0 = normal operation of the DDS phase accumulator (default). 1 = synchronously resets the DDS phase accumulator anytime I/O_UPDATE is asserted or a profile change occurs.

Bit(s)	Mnemonic	Description
12	Clear DRG	0 = Normal operation of the Digital Ramp Generator (default). 1 = Asynchronous, static reset of the DRG accumulator. The ramp accumulator remains reset as long as this bit remains set. This bit is synchronized with either an I/O_UPDATE or a PROFILE[2:0] change and the next rising edge of SYNC_CLK.
11	Clear phase accumulator	0 = Normal operation of the DDS phase accumulator (default). 1 = Asynchronous, static reset of the DDS phase accumulator.
10	Open	Ineffective unless CFR1[8] = 1.
9	Select auto OSK	0 = manual OSK enabled (default). 1 = automatic OSK enabled.
8	OSK enable	0 = OSK disabled (default). 1 = OSK enabled.
7	DIGITAL power down	This bit is effective without the need for an I/O update. 0 = clock signals to the digital core are active (default). 1 = clock signals to the digital core are disabled.
6	DAC power down	0 = DAC clock signals and bias circuits are active (default). 1 = DAC clock signals and bias circuits are disabled.
5	REFCLK input power-down	This bit is effective without the need for an I/O update. 0 = REFCLK input circuits and PLL are active (default). 1 = REFCLK input circuits and PLL are disabled.
4	Open	
3	External power-down control	0 = assertion of the EXT_PWR_DWN pin affects full power-down (default). 1 = assertion of the EXT_PWR_DWN pin affects fast recovery power-down.
2	Open	
1	SDIO input only	0 = configures the SDIO pin for bidirectional operation; 2-wire serial programming mode (default). 1 = configures the serial data I/O pin (SDIO) as an input only pin; 3-wire serial programming mode.
0	LSB first	0 = configures the serial I/O port for MSB-first format (default). 1 = configures the serial I/O port for LSB-first format.

Control Function Register 2 (CFR2)—Address 0x01

Four bytes are assigned to this register.

Table 6. Bit Descriptions for CFR2

Bit(s)	Mnemonic	Description
31:24	Open	
23	Profile enable	See the **In** digital ramp modulation mode, the modulated DDS signal control parameter is supplied directly from the digital ramp generator (DRG). The ramp generation parameters are controlled through the serial or parallel I/O port. **The ramp generation parameters** allow the user to control both the rising and falling slopes of the ramp. The upper and lower boundaries of the ramp, the step size and step rate of the rising portion of the ramp, and the step size and step rate of the falling portion of the ramp are all programmable. The ramp is digitally generated with 32-bit output resolution. The 32-bit output of the DRG can be programmed to affect frequency, phase, or amplitude. When programmed for frequency, all 32 bits are used. However, when programmed to for phase or amplitude, only the 16 MSBs or 12 MSBs, respectively, are used. The ramp direction (rising or falling) is externally controlled by the DRCTL pin. An additional pin (DRHOLD) allows the user to suspend the ramp generator in its present state. Note, amplitude control must also be enabled using the OSK EN bit in register CFR1

Bit(s)	Mnemonic	Description
		Parallel Data Port Modulation Mode section for more details. 0 = disables Profile functionality (default). 1 = enables Profile functionality.
22	Parallel data enable	See the **In** digital ramp modulation mode, the modulated DDS signal control parameter is supplied directly from the digital ramp generator (DRG). The ramp generation parameters are controlled through the serial or parallel I/O port. **The ramp generation parameters** allow the user to control both the rising and falling slopes of the ramp. The upper and lower boundaries of the ramp, the step size and step rate of the rising portion of the ramp, and the step size and step rate of the falling portion of the ramp are all programmable. The ramp is digitally generated with 32-bit output resolution. The 32-bit output of the DRG can be programmed to affect frequency, phase, or amplitude. When programmed for frequency, all 32 bits are used. However, when programmed to for phase or amplitude, only the 16 MSBs or 12 MSBs, respectively, are used. The ramp direction (rising or falling) is externally controlled by the DRCTL pin. An additional pin (DRHOLD) allows the user to suspend the ramp generator in its present state. Note, amplitude control must also be enabled using the OSK EN bit in register CFR1 Parallel Data Port Modulation Mode section for more details. 0 = disables parallel data port modulation functionality (default). 1 = enables parallel data port modulation functionality.
21:20	Digital ramp destination	See Table xx for details. Default is 00b. See the **Digital Ramp Generator (DRG)** section for details.
19	Digital ramp enable	0 = disables digital ramp generator functionality (default). 1 = enables digital ramp generator functionality.
18	Digital ramp no-dwell high	See the **Digital Ramp Generator (DRG**) section for details. 0 = disables no-dwell high functionality (default). 1 = enables no-dwell high functionality.
17	Digital ramp no-dwell low	See the **Digital Ramp Generator (DRG**) section for details. 0 = disables no-dwell low functionality (default). 1 = enables no-dwell low functionality.
16	Open	
15	Matched latency enable	0 = simultaneous application of amplitude, phase, and frequency changes to the DDS arrive at the output in the order listed (default). 1 = simultaneous application of amplitude, phase, and frequency changes to the DDS arrive at the output simultaneously.
14	Frequency Jump Enable	
13	DR_OVR	
12	Open	
11	SYNC_CLK enable	0 = the SYNC_CLK pin is disabled and forced to a static Logic 0 state; the internal clock signal continues to operate and provide timing to the data assembler. 1 = the internal SYNC_CLK signal appears at the SYNC_CLK pin (default).
10	SYNC_CLK invert	0 = normal SYNC_CLK polarity; Q-data associated with Logic 1, I-data with Logic 0 (default). 1 = inverted SYNC_CLK polarity.

Bit(s)	Mnemonic	Description
9 8 7:0	MCS Onetime shot Enable SYNC_OUT enable Open	0 = the SYNC_OUT pin is disabled; static Logic 0 output. 0 = the SYNC_OUT pin is disabled; static Logic 0 output.

OUTLINE DIMENSIONS



Figure xx. 88-Lead Lead Frame Chip Scale Package, Exposed Pad [LFCSP_VQ]
12 x 12 mm Body, Very Thin Quad
(CP-88-5)
Dimensions shown in millimeters

PR10837-0-6/12(PrI)